

# VISTA 128FB Programming Form

Some fields are programmed for each partition (shown as shaded fields). If Programming a Multiple Partition System, see the PARTITION-SPECIFIC section for programming these fields. Standard default (\*97) values are shown in brackets [ ], otherwise default = 0.

**\*00** INSTALLER CODE   
Enter 4 digits, 0-9 [5140]

**\*08** TEMPORAL SIREN PULSE [0]   
1 = Yes; 0 = No

**\*09** ENTRY DELAY #1 [02]   
00-15 times 15 seconds  
Maximum "03" for UL Commercial Burglary installations.

**\*10** EXIT DELAY #1 [03]   
00-15 times 15 seconds  
Maximum "04" for UL Listed installations.

**\*11** ENTRY DELAY #2 [06]   
00-15 times 15 seconds (must be longer than Entry Delay #1).  
Maximum "03" for UL Commercial Burglary installations.

**\*12** EXIT DELAY #2 [08]   
00-15 times 15 seconds (must be longer than Exit Delay #1)  
Maximum "04" for UL Commercial Burglary installations.

**\*13** BELL 1 TIMEOUT [04]   
01-15 times 2 minutes. Minimum 16 min. for UL Commercial Burglary and 6 min. for Commercial Fire.

**\*15** KEYSWITCH ASSIGNMENT [0]   
Enter partition in which keyswitch used,  
1-8; 9=Silences bells if fire present; 0=disable

**\*16** BELL 1 CONFIRMATION OF ARMING DING [0]   
1=enable; 0=disable. Must be "1" for UL Burglary Installations.

**\*17** AC LOSS KEYPAD SOUNDING [0]   
1=yes; 0=no

**\*19** RANDOMIZE AC LOSS REPORT [2]   
1=10-40 min; 2=6-12 hrs; 0=normal report (about 2 min. after AC loss). Must be "2" for Central and Remote Station Fire alarm systems.

**\*20** VIP MODULE PHONE CODE   
Enter 01 - 09 for the first digit; enter [00] , [11] 11 for "\*" or 12 for "#" for the second digit. This field Must be set to "0" for Commercial Fire & UL Commercial Burglary installations.

**\*22** KEYPAD PANIC ENABLE [001]   
1=enable; 0=disable 995 996 999

**\*23** MULTIPLE ALARMS [1]   
1=yes; 0=no

**\*24** IGNORE EXPANSION ZONE TAMPER [0]   
1=Ignore; 0=Enable tamper for RF and RPMs. Must be "0" for UL installations if using these devices.

**\*25** BURG.TRIGGER FOR RESPONSE TYPE 8 [1]   
1=enable; 0=disable

**\*26** INTELLIGENT TEST REPORTING [0]   
1=yes, (no report sent if any other report was recently sent); 0=no.. Must be 0 for Commercial Fire & UL Commercial Burglary.

**\*27** TEST REPORT INTERVAL [024]   
Enter interval in hours, 001-999; 000=no report ; Max. 024 for Commercial Fire & UL.

**\*28** POWER UP IN PREVIOUS STATE [1]   
1=yes; 0=no; "1" for UL.

**\*29** QUICK ARM [1]   
1=yes; 0=no

**\*30** MAIN DIALER (TOUCHTONE OR ROTARY) [0]   
1=TouchTone; 0=rotary

**\*31** PABX ACCESS CODE   
00-09; B-F (11-15)

**\*32** PRIM. SUBS. ACCT #   
Enter 00-09; B-F (11-15) [15 15 15 15]

**\*33** PRIMARY PHONE NUMBER  
  
  
Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*34** SECONDARY PHONE NUMBER  
  
  
Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*35** DOWNLOAD PHONE No.  
  
  
Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*36** DOWNLOAD ID No.  
  
Enter 00-09; A-F (10-15) [15 15 15 15 15 15 15 15]

**\*37 DOWNLOAD COMMAND ENABLES**

Dialer System Not Remote Remote Remote UploadDownload  
 Shutdwn Shutdwn Used Bypass Disarm Arm Program Program  
 See field 1\*53 for Callback disable option; [1=enable];  
 0=disable; For Commercial Fire & UL installations, all  
 entries must be "0."

**\*38 PREVENT ZONE XXX BYPASS** [000]     
 001-128; 00 if all zones can be bypassed

**\*39 ENABLE OPEN/CLOSE REPORT FOR INSTALLER CODE** 1=enable; 0=disable [1]

**\*40 OPEN/CLOSE REPORT FOR KEYSWITCH** [0]   
 1=enable; 0=disable

**\*41 NORMALLY CLOSED or EOLR (Zones 3-8)** [0]   
 1=N.C.loops; 0=EOLR supervision; Must be "0" for Commercial Fire & UL.

**\*42 DIAL TONE PAUSE** [0]   
 0=5 seconds; 1=11 seconds; 2=30 seconds; Must be "0" Commercial Fire & UL.

**\*43 DIAL TONE DETECTION** [1]   
 1=wait for true dial tone; 0=pause, then dial

**\*44 RING DETECTION COUNT** [00]    
 01-14; 15=answering machine; 00=no detection. Must be "00" for Commercial Fire & UL Burglary.

**\*45 PRIMARY FORMAT** [0]   
 0=Low Speed; 1=Contact ID; 2=Ademco High Speed; 3=Ademco Express

**\*46 LOW SPEED FORMAT (Primary)** [0]   
 0=Ademco Low Speed; 1=Sescoa/Radionics

**\*47 SECONDARY FORMAT** [0]   
 0=Low Speed; 1=Contact ID; 2=Ademco High Speed; 3=Ademco Express

**\*48 LOW SPEED FORMAT (Sec.)** [0]   
 0=Ademco Low Speed; 1=Sescoa/Radionics

**\*49 CHECKSUM VERIFICATION** [0] [0]    
 1=yes; 0=no Prim Sec

**\*50 SESCOA/RADIONICS SELECT** [0]   
 1=Sescoa; 0=Radionics

**\*51 DUAL REPORTING** [0]   
 1=yes; 0=no If used with Spilt Reporting "1" option (1\*34), alarms and alarm restores go to both primary & secondary numbers, while all other reports go to secondary only. If used with Split Reporting "2" option, alarms and alarm restores go to both, open/close and test messages go to secondary only, while all other reports go to primary. If used with Split Reporting "3" option, fire alarms and fire supervisory signals go to both primary and secondary, while all other reports go to secondary only.

**\*52 STANDARD/EXPANDED REPORT FOR PRIMARY**

[0 0 0 0 0 0]        
 Alarm Rstr Bypass Trbl Opn/Cls Low Bat  
 0=standard; 1=expanded;  
 Note: Expanded overrides 4+2 format.

**\*53 STANDARD/EXPANDED REPORT FOR SECONDARY**

[0 0 0 0 0 0]        
 Alarm Rstr Bypass Trbl Opn/Cls Low Bat  
 0=standard; 1=expanded;  
 Note: Expanded overrides 4+2 format.

**\*56 USE LRR ONLY** [0]   
 0=No, 1=Yes, if built-in dialer will not be used.

**\*57 LRR IF DIALER FAILS** [0]   
 0=No, 1=Yes, if radio is to be used as a backup to dialer

**\*58 LRR ENABLE CS #1**  
 [0 0 0 0 0 0]        
 Alarm Trbl Byp O/C Syst Tst  
 0=disable, 1=enable for reports for primary subs id of LRR

**\*59 LRR ENABLE CS#2**  
 [0 0 0 0 0 0]        
 Alarm Trbl Byp O/C Syst Tst  
 0=disable, 1=enable for reports for secondary subs id of LRR

**\*64 PAGER INSTALLED** [0]   
 0=No, 1=Yes, alpha numeric pager interface is installed.

**\*65 PAGER PHONE # FOR ALARMS**  
           
       
 Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*66 PAGER ID # FOR ALARMS**  
           
 Enter up to 10 digits for the pager id #

**\*67 PAGER PHONE # FOR SUPERVISION**  
           
       
 Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*68 PAGER ID # FOR SUPERVISION**  
           
 Enter up to 10 digits for the pager id #

**\*69 PAGER PHONE # FOR BYPASSES**  
           
       
 Enter 0-9 for each digit. Enter #11 for \*, #12 for #, #13 for 2 second pause

**\*70 PAGER ID # FOR BYPASSES**  
           
 Enter up to 10 digits for the pager id #



- 1\*35 ACCESS CONTROL DIALER ENABLES**  
 [0 0 0 0 0]        
Dialer Trbl Byps Not used Syst Alm  
 1=enable; 0=disable
- 1\*42 CALL WAITING DEFEAT** [0]   
 1=Yes; 0=No.
- 1\*43 PERM. KEYPAD BACKLIGHT** [0]   
 1=enable; 0=disable When disabled, display lights when any key is pressed, and turns off after period of keypad inactivity.
- 1\*44 WIRELESS KEYPAD** [0]   
 TAMPER DETECT ENABLE 1=enable; 0=disable. Must be "0" for Commercial Fire and UL installations.
- 1\*45 EXIT DELAY SOUNDING** [0]   
 1=enable; 0=disable. Produces quick beeping during exit delay if enabled.
- 1\*47 CHIME ON BELL 1** [0]   
 1=enable; 0=disable
- 1\*48 WIRELESS KEYPAD ASSIGNMENT** [0]   
 0=disable; enter partition in which RF keypad used, 1-8. Must be "0" for Commercial Fire and UL installations.
- 1\*49 SUPPRESS TX SUPERVISION SOUND** [1]   
 1=disable; 0=enable. Must be "0" for Commercial Fire and UL installations.
- 1\*52 SEND CANCEL IF ALARM + OFF** [0]   
 1=no restriction; 0=within bell timeout period only
- 1\*53 DOWNLOAD CALLBACK** [0]   
 1=callback not required; 0=callback required; Must be "0" for Commercial Fire and UL installations.
- 1\*56 50/60 Hz CLOCK SPEED** [0]   
 1=50 Hz; 0=60 Hz.
- 1\*57 ENABLE 5800 RF BUTTON GLOBAL ARM** [0]   
 1=enable; 0=disable
- 1\*58 5800 RF BUTTON FORCE ARM** [0]   
 Enter "1" to enable. If a zone is faulted after pressing button, console will beep once. User should press button again within 4 sec. to force bypass those zones. Enter "0" to disable.  
 Must be "0" for Commercial Fire and UL installations.
- 1\*60 ZONE 5 AUDIO ALARM VERIFICATION** [0]   
 Enter 1 if 2-way audio (AAV) is being used; Enter 0 if it is not.  
 Must be "0" for Commercial Fire and UL installations.
- 1\*70 EVENT LOG TYPES**  
 [1 0 0 0 1 0]        
Alrm Chck Byps O/C Syst Test  
 1=enable; 0=disable
- 1\*71 12/24 HOUR TIME STAMP FORMAT** [0]   
 0=12 hour; 1=24 hour
- 1\*72 EVENT LOG PRINTER ON-LINE** [0]   
 0=disable; 1=enable

- 1\*73 PRINTER BAUD RATE** 1=300; 0=1200 [0]   
 Must be 1200 if using pager interface
- 1\*74 RELAY TIMEOUT XX MINUTES** [000]   
 Enter the relay timeout, **0-127** in multiples of 2 minutes, desired for #80 Menu Mode time driven event relay command numbers "04/09" and #93 Menu Mode Output Programming command "56".
- 1\*75 RELAY TIMEOUT YY SECONDS** [000]   
 Enter the relay timeout, **0-127** seconds, desired for #80 Menu Mode time driven event relay command numbers "05/10" and #93 Menu Mode Output Programming command "57".
- 1\*76 ACCESS CONTROL RELAY FOR PART.** [00]   
 Relay will be pulsed for 2 seconds whenever code + [0] is pressed. Enter 00-96; 00=none. Must be "00" for Commercial Fire & UL..
- 1\*77 LOG FIRST MAINTENANCE SIGNAL** [0]   
 0=No Log; 1=Log first maintenance signal from each smoke detector

**3rd Page Programming Fields (press \*94)**

- 2\*00 NUMBER OF PARTITIONS** [1]   
 Enter 1-8
- 2\*01 DAYLIGHT SAVINGS TIME** [04, 10]    
 START/END MONTH Start End  
 00-12; if no daylight savings time, enter 00,00
- 2\*02 DAYLIGHT SAVINGS TIME** [1, 5]   
 START/END WEEKEND # Start | End  
 Enter 1-7. 1=first; 2=second; 3=third; 4=fourth; 5=last; 6=next to last; 7=3rd from last [1,5; 1st Sunday in April, last in Oct.]
- 2\*05 AUTO-ARM DELAY** [15]   
 Enter the time between the end of the arming window and the start of auto-arming warning period, in values of 1-14 times 4 minutes 00=instant; [15=no auto arm at all]. When this delay expires, the Auto-Arm Warning Period begins.
- 2\*06 AUTO-ARM WARNING PERIOD** [15]   
 This is the time during which the user is warned to exit the premises prior to the auto-arming of the system (beeps every 15 seconds; "ALERT" displayed). Enter 01-15 minutes. 00=instant at end of arming delay .
- 2\*07 AUTO-DISARM DELAY** [15]   
 This is the time between the end of the disarming window and the start of auto-disarming. Enter 01-14 times 4 minutes; 00=instant at end of window; 15=no auto-disarm.
- 2\*08 ENABLE FORCE ARM FOR AUTO-ARM** [0]   
 0=disable; 1=enable
- 2\*09 OPEN/CLOSE REPORTS BY EXCEPTION** [0]   
 1=enable; 0=disable; If enabled, only openings and closings occurring outside the scheduled opening/closing windows will trigger dialer reports. Opening reports will also be suppressed during the closing window, in order to prevent false reports when the user arms the system and then reenters the premises to retrieve a forgotten item.

**2\*10** ALLOW DISARMING ONLY DURING [0]

**ARMING/DISARMING WINDOWS**

0=disable; 1=enable

See system-wide field 2\*11 if enabling field 2\*10. This feature adds high security to the installation.

**2\*11** ALLOW DISARM OUTSIDE WINDOW [0]

**IF ALARM OCCURS**

Used only if field 2\*10 (partition-specific field) is set to "1". If this field is enabled ("1") the system can be disarmed outside the disarm window if an alarm has occurred. If "0", disarming can only be done during the disarm window. If field 2\*10 is set to "0" for a partition, this field has no effect for that partition.

**2\*18** ENABLE GOTO FOR THIS PARTITION [0]

1=Allow log-on from other partitions; 0=disable

**2\*19** USE PARTITION DESCRIPTORS [0]

0=disable; 1=enable

**2\*20** ENABLE J2 TRIGGERS by PARTITION [1]

0=disable for displayed partition; 1=enable for displayed partition

**2\*21** ENABLE SUPERVISION PULSES FOR LRR

TRIGGER OUTPUTS [00000]       
F B P S T

Used for supervised connection to 7920SE. Enter 0 to disable or 1 to enable the listed outputs. F= Fire; B= Burglary; S= Silent panic/duress. Enter 1 for Commercial Burglary and UL.

**2\*22** DISPLAY FIRE ALARMS OF [0]

**OTHER PARTITIONS**

0=No; 1=Yes.

**2\*23** DISPLAY BURG & PANIC ALARMS OF [0]

**OTHER PARTITIONS**

0=No; 1=Yes.

**2\*24** DISPLAY TROUBLES OF OTHER [0]

**PARTITIONS**

0=No; 1=Yes.

**4th Page Programming Fields (press \*94)**

**3\*00** DISPLAY TRBL INSTEAD OF CHECK [0]

**3\*01** FIRE DISPLAY LOCK [0]

0=scroll all alarms; 1=lock display of first fire alarm.

**3\*12** ZN TYPE 18 DELAY USE [1]

0=Check Displayed; 1=Trbl Displayed

**3\*13** SUPV. N.O./N.C. SELECTION [0]

0=Supv. on short/trouble on open; 1=supv. on short or open

**3\*14** WATERFLOW SILENCE OPTION [0]

0=Silence on Code + OFF; 1=Silence when waterflow restores

**3\*15** ALARM BELL SOUND [1,0]

0=pulsed; 1=steady

Bell 1 Bell 2

**3\*16** DELAY for ZONE TYPES 17 & 18 [00]

(Waterflow & Fire Supv) Enter 00-15 times 2 seconds

**3\*17** ALTERNATE FUNCTION (TAMPER) [0]

FOR ZONE 6 0=disabled; 1=enabled

**3\*18** EXTENDED DELAY FOR TYPES 17&18 [0]

0=No; 1=Yes

**3\*19** ENABLE J2 HEADER PRINTER PORT [0]

0=pins 5&9 function as per field 3\*20; 1=pins 5&9 act as printer RXD & DTR

**3\*20** TRIGGER OUTPUTS SELECTION [0]

0= LORRA full connection & Remote Console Sounder; 1=LORRA limited conn. & Keyswitch LEDs; 2=LORRA fire only conn. & 5140LED

**3\*21** MAX # OF DIALER ATTEMPTS [8]

1-8 (3, 4 or 5 for NFPA72 compliant systems when a secondary phone number is programmed (field \*34)

**3\*30** DIALER SELECTION [1,0]

1=enabled; 0=disabled

Main Backup

**3\*31** BACKUP DIALER TOUCHTONE/ROTARY [0]

1=TouchTone; 0=Rotary

**3\*50** ZONE TYPE RESTORE ENABLES

FOR ZONE TYPES 16-18

16 17 18

1 = enabled; [0 = disabled]

**3\*55** RESET ON SECOND OFF FOR BELL 1 [0]

1 = enabled; 0 = disabled

**3\*56** RESET ON SECOND OFF FOR BELL 2 [0]

1 = enabled; 0 = disabled

**3\*57** BELL 2 & AUX. RELAY CONFIRM

**ARM DING**

Bell 2 AUX.

1=enable; [0=disable] . Must be 1 for UL Commercial Burglary.

**3\*59** ENABLE BELL 2 & AUX. RELAY

**CHIME ANNUNCIATION**

Bell 2 AUX

1=enable; [0=disable]

**3\*60** BELL 2 & AUX. RELAY TIMEOUT

00-15 times 2 minutes; 00=no timeout [00,00] Bell 2 AUX Must be minimum of 16 minutes for UL Burglary installations.

**3\*61** AUX. RELAY FUNCTION [1]

0=Trouble/supervisory; 1=Alarm, silenced by code + OFF 2=Smoke Detector Reset; 3=Battery Save; 4=Alarm, silenced by code + [#] + 67

**3\*82** ENABLE BURG. FEATURES ON PART. 1 [1]

1=enable; 0=disable; "0" disables AWAY, STAY, MAX, TEST, INSTANT & CHIME functions

**3\*85** ENABLE FIRE & SYSTEM ZONE BYPASS [1]

0=not enabled; 1=only installer can bypass; 2=only installer & master user can bypass. Applies to fire zone types 9, 16, 17 & 18 and system zones 970-977. Applies to Partition 1 only.

## SUMMARY OF PROGRAMMING COMMANDS

- **To enter program mode**, enter installer code + [8] + [0] + [0] + [0]
- **To set standard defaults**, press \*97
- **To change to next page of program fields**, press \*94
- **To return to previous set of fields**, press \*99
- **To erase account & phone number field entries**, press [\*] + field number + [\*]
- **To assign zone descriptors**, press #93 + follow menu prompts
- **To add custom words**, press #93 + follow menu prompts
- **To enter Installer's Message**, press #93 + follow menu prompts
- **To exit program mode**, press \*99 OR \*98: \*99 allows re-access to programming mode by installer code. \*98 prevents re-access to programming mode by installer code.

# Partition-Specific Fields

(Duplicate this page for each partition in the installation.)

To program these fields,

1. Press \*91 to select a partition.
2. Enter a partition-specific field number (ex. \*09).
3. Make the required entry.
4. Repeat steps 1-3 for each partition in the system.

## PARTITION # \_\_\_\_\_ PROGRAM FIELDS

### 1st Page Fields

- \*09** ENTRY DELAY #1 [02]    
 00-15 times 15 seconds. Maximum 03 for UL Listed installations.
- \*10** EXIT DELAY #1 [03]    
 00-15 times 15 seconds. Maximum 04 for UL Listed installations.
- \*11** ENTRY DELAY #2 [06]    
 00-15 times 15 seconds. Maximum 03 for UL Commercial Burglary installations.
- \*12** EXIT DELAY #2 [08]    
 00-15 times 15 seconds. Maximum 04 for UL Commercial Burglary installations.
- \*13** BELL 1 TIMEOUT [04]    
 01-15 times 2 minutes. Minimum 16 minutes for UL Commercial Burglary and 6 minutes for Commercial Fire installations.
- \*16** CONFIRMATION OF ARMING DING [0]   
 1=enable; 0=disable. Must be "1" for UL Commercial Burglary installations.
- \*22** KEYPAD PANIC ENABLES [001]     
 1=enable; 0=disable 995 996 999
- \*23** MULTIPLE ALARMS [1]   
 1=yes; 0=no. Enter 1 for Commercial Fire & UL Commercial Burglary installations.
- \*29** QUICK ARM [1]   
 1=yes; 0=no
- \*32** PRIM. SUBS. ACCT #      
 Enter 00-09; B-F (11-15) [15 15 15 15]
- \*38** PREVENT ZONE XXX BYPASS [000]     
 001-128; 000 if all zones can be bypassed
- \*39** ENABLE OPEN/CLOSE REPORT FOR INSTALLER CODE [1]   
 1=enable; 0=disable
- \*84** SWINGER SUPPRESSION [03]    
 01-15 alarms; Must be "00" (disabled) for Commercial Fire & UL installations..

- \*85** ENABLE DIALER REPORTS [0]      
 FOR PANICS & DURESS 995 996 999 Duress  
 1=enable; 0=disable
- \*87** ENTRY WARNING [0]   
 1=continuous; 0=3 beeps
- \*88** BURG. ALARM COMM. DELAY [0]    
 1=16 seconds; 0=no delay. Must be "0" for UL Commercial Burglary installations.
- \*90** SEC. SUBS. ACCT #      
 Enter 00-09; B-F (11-15) [15 15 15 15]
- 1\*18** AFFECTS LOBBY [0]   
 Enter 1 if this partition affects the common lobby; enter 0 if it does not.
- 1\*19** ARMS LOBBY [0]   
 Enter 1 if arming this partition attempts to arm lobby; enter 0 if it does not

### 2nd Page Fields

- 1\*26** PANIC BUTTON OR SPEEDKEY [00, 00, 00, 00]      
 A B C D  
 Enter speedkey macro # (01-35) to use keys A-C for macro. Otherwise enter 00 to use as panic. For D key, enter macro # or 00 to select macro when key is pressed.
- 1\*43** PERM. KEYPAD BACKLIGHT [0]   
 1=enable; 0=disable When disabled, display lights when any key is pressed, and turns off after period of keypad inactivity.
- 1\*45** EXIT DELAY SOUNDING [0]   
 1=enable; 0=disable Produces quick beeping during exit delay if enabled.
- 1\*47** CHIME ON BELL 1 [0]   
 1=enable; 0=disable
- 1\*52** SEND CANCEL IF ALARM + OFF [0]   
 1=no restriction; 0=within Bell Timeout period only
- 1\*76** ACCESS CONTROL RELAY FOR PART. [00]    
 Relay will be pulsed for 2 seconds whenever code + [0] is pressed. Enter 00-96; 00=none. Must be "00" for Commercial Fire & UL.

### 3rd Page Fields

**2\*05** AUTO-ARM DELAY [15]

Enter the time between the end of the arming window and the start of auto-arming warning period, in values of 1-14 times 4 minutes 00=instant; [15=no auto arm at all]. When this delay expires, the Auto-Arm Warning Period begins.

**2\*06** AUTO-ARM WARNING PERIOD [15]

This is the time during which the user is warned to exit the premises prior to the auto-arming of the system (beeps every 15 seconds; "ALERT" displayed). Enter 01-15 minutes. 00=instant at end of arming delay .

**2\*07** AUTO-DISARM DELAY [15]

This is the time between the end of the disarming window and the start of auto-disarming. Enter 01-14 times 4 minutes; 00=instant at end of window; 15=no auto-disarm.

**2\*08** ENABLE FORCE ARM FOR AUTO-ARM [0]

0=disable; 1=enable.

**2\*09** OPEN/CLOSE REPORTS BY EXCEPTION [0]

1=enable; 0=disable; If enabled, only openings and closings occurring outside the scheduled opening/closing windows will trigger dialer reports. Opening reports will also be suppressed during the closing window, in order to prevent false reports when the user arms the system and then reenters the premises to retrieve a forgotten item.

**2\*10** ALLOW DISARMING ONLY DURING [0]

ARMING/DISARMING WINDOWS  
See system-wide field 2\*11 if enabling field 2\*10. This feature adds high security to the installation.  
0=disable; 1=enable

**2\*18** ENABLE GOTO FOR THIS PARTITION [0]

1=Allow log-on from other partitions; 0=disable

**2\*20** ENABLE J2 TRIGGERS by PARTITION [1]

0=disable for displayed partition; 1=enable for displayed partition

**2\*22** DISPLAY FIRE ALARMS OF [0]

OTHER PARTITIONS  
0=No; 1=Yes

**2\*23** DISPLAY BURG/PANIC ALARMS OF [0]

OTHER PARTITIONS  
10=No; 1=Yes

**2\*24** DISPLAY TROUBLES OF OTHER [0]

PARTITIONS  
0=No; 1=Yes

### 4th Page Fields

**3\*57** BELL 2 & AUX. RELAY CONFIRM    
ARM. DING 1=enable; [0=disable] Bell 2 Relay  
Must be "1" for UL.

**3\*59** ENABLE BELL 2 & AUX. RELAY    
CHIME ANNUNCIATION 1=enable; [0=disable] Bell 2 Relay

**3\*60** BELL 2 & AUX. RELAY TIMEOUT      
00-15 times 2 minutes; 00=no timeout [00,00] Bell 2 Relay  
Minimum 16 min. for UL Burglary installations.

### SUMMARY OF PROGRAMMING COMMANDS

- **To enter program mode**, enter installer code + [8] + [0] + [0] + [0]
- **To set standard defaults**, press \*97
- **To change to next page of program fields**, press \*94
- **To return to previous set of fields**, press \*99
- **To erase account & phone number field entries**, press [\*] + field number + [\*]
- **To assign zone descriptors**, press #93 + follow menu prompts
- **To add custom words**, press #93 + follow menu prompts
- **To enter Installer's Message**, press #93 + follow menu prompts
- **To exit program mode**, press \*99 OR \*98: \*99 allows re-access to programming mode by installer code. \*98 prevents re-access to programming mode by installer code.