

# AlarmNet - Stand Alone Video Setup



12-22-2010

## HSC - AlarmNet® Services

Welcome AlarmNet Dealer.

[Help: AlarmNet Direct User Guide](#)

Wednesday, December 22, 201

- >Introduction
- Show Programmed Devices GSM/I
- Show Programmed Devices GSM/I (for ADT-Direct ONLY)
- SIM Activation/Status
- CMC Configuration (for ADT-Direct ONLY)
- Program New Device GSM/I
- Replace Other Device
- Program New Device GSM/I (for ADT-Direct ONLY)
- Program New Device GSM NODE
- My Profile
- Manage Users
- My History
- Web Design Tool
- GSM Coverage Map United States
- GSM Coverage Map Canada
- Feedback
- Return to AlarmNet Direct
- Logout



HSC - AlarmNet® Services

Welcome John Stachurski.

[Help: Program New Device GSM/I](#)

Monday, June 14, 2010

[Help: Program New Device Vista-21iP and Vista-GSM](#)

- Introduction
- Show Programmed Devices
- GSM/I
- SIM Activation/Status
- >Program New Device GSM/I
- Replace Other Device
- My Profile
- Manage Users
- My History
- Web Design Tool
- GSM Coverage Map United States
- GSM Coverage Map Canada
- Feedback
- Logout

Enter Account Information For New Device

Video Services Only

← Check the Video Services only Check Box

Primary City ID :

Primary CSID :

Primary Subscriber :

Dual Reporting

Enter GSM/I Information For New Device

Supervision :

MAC ID :  -  -  -  -  -  MAC CRC :

Enable Remote Services [Help: Total Connect Setup](#) [Help: Hints For Total Connect](#)

Enable Voice Service

**CLICK "ADVANCED PROGRAMMING" TO PROGRAM:**

- UL864 COMMERCIAL FIRE WITH AN IGSMCF
- ULC COMMERCIAL FIRE AND BURG. WITH AN IGSMCN
- OR "HIGH USAGE" PRICE PLAN OPTION

## HSC - AlarmNet® Services

Welcome John Stachurski.

[Help: Program New Device GSM/I](#)

Monday, June 14, 2010

[Help: Program New Device Vista-21iP and Vista-GSM](#)

<b>Introduction</b>
<b>Show Programmed Devices GSM/I</b>
<b>SIM Activation/Status</b>
<b>&gt;Program New Device GSM/I</b>
<b>Replace Other Device</b>
<b>My Profile</b>
<b>Manage Users</b>
<b>My History</b>
<b>Web Design Tool</b>
<b>GSM Coverage Map United States</b>
<b>GSM Coverage Map Canada</b>
<b>Feedback</b>
<b>Logout</b>

Enter Account Information For IP Video

**Video Services Only**

**Primary City ID :**

**Primary CSID :**

**Primary Subscriber :**

Use a New GSM/I account number. Enter in your City ID, CS ID, and 4 digit acct. number.

**NOTE: FURTHER ACTION ON "SHOW PROGRAMMED DEVICES GSM/I" PAGE IS REQUIRED TO COMPLETE THE STANDALONE FUNCTIONALITY.**

Done

Select Done

## HSC - AlarmNet® Services

Welcome John Stachurski.

(Eastern Time is shown for all transferred times)

Monday, June 14, 2010

- Introduction
- > Show Programmed Devices GSM/I
- SIM Activation/Status
- Program New Device GSM/I
- Replace Other Device
- My Profile
- Manage Users
- My History
- Web Design Tool
- GSM Coverage Map United States
- GSM Coverage Map Canada
- Feedback
- Logout

SEARCH BY:

Acct #:       MAC ID:

Status:     Remote Service:

Acct. Key: Not Registered Registered Video Svcs.

MAC ID Key: (Move cursor over images)

Results [1 - 1] of 1; Page 1 of 1

Acct #	MAC ID	Device Type	Transferred (ET)	Actions
99 76 0004	Video Service Acct. 	N/A	N/A	<input type="button" value="EndUser-Add"/> <input type="button" value="GO"/>

Select GO to Add an End User

« First   « Previous

Pick a Page:

Next »   Last »

## Honeywell Security & Custom Electronics – AlarmNet® Services

[Return to Show Programmed Devices page](#)

### Processing of End-User Form


Choose End-User (New or Pre-Existing).  
Please complete all fields within this form and submit to process.

**Upon submittal, an email confirmation will be sent to the end-user.**

#### Choose End-User type:

- Click here to create a new End-User
- Click here to merge with an existing End-User

Select Create a New  
End User



[Return to Show Programmed Devices page](#)

**Additional Address Information : (Optional)**

**City : (Optional)**

**Country :**  **State / Province :**

**Zip / Postal Code : (Optional)**

---

**END-USER LOGIN INFORMATION:**

**First Name : (Required)**

**Last Name : (Required)**

**E-mail address : (Required)**

**User Phone (include area code) : (Optional)**

-  -

**User Name : (Required)**

(Only letters(A-Z) / numbers(0-9) allowed, letters and numbers must both be included, minimum length of 8)

**Password : (Required)**

(Only letters(A-Z) / numbers(0-9) allowed, letters and numbers must both be included, minimum length of 8)  
(Username and Password must be different)

**Confirm Password : (Required)**

(Only letters(A-Z) / numbers(0-9) allowed, letters and numbers must both be included, minimum length of 8)

[View Programmed Devices page](#)

Enter Device name, First name, Last name, and email address of end user

Select Submit  
End user will receive an email with Total Connect URL address and a username and password

### HSC - AlarmNet® Services

Welcome John Stachurski.

(Eastern Time is shown for all transferred times)

Monday, June 14, 2010

- Introduction
- > Show Programmed Devices GSM/I
- SIM Activation/Status
- Program New Device GSM/I
- Replace Other Device
- My Profile
- Manage Users
- My History
- Web Design Tool
- GSM Coverage Map United States
- GSM Coverage Map Canada
- Feedback
- Logout

**SEARCH BY:**

Acct #:       MAC ID:

Status:     Remote Service:

Acct. Key: Not Registered Registered Video Svcs.

MAC ID Key: (Move cursor over images)

Results [1 - 1] of 1; Page 1 of 1

Acct #	MAC ID	Device Type	Transferred (ET)	Actions
99 76 0004	Video Service Acct. 	N/A	N/A	<input type="button" value="Video-Config"/> <input type="button" value="GO"/>

From Show Programmed Device menu select Video-Configure and Select GO

« First   « Previous

Pick a Page:

Next »   Last »

[Return to Show Programmed Devices page](#)

Refresh Page

**Video Device Management**

Action	Type	Name of Video device	Mac	Last Check In	Version
--------	------	----------------------	-----	---------------	---------

No video devices are linked to this account

**Add an IP Camera to Account 86-87-0523**

**VIDEO MAC ID :**  
00 - C0 - 02 -  -  -

**Video Device Name :**

Enter in last six values of the MAC ID located on the camera carton or on the back of the camera, then add a name for the camera.

Select Add Video Device.  
End user will now be able to view their cameras on the Total Connect web site  
You can add up to six cameras per account number.  
The End user will receive an email when a new camera has been added or deleted

[Return to Show Programmed Devices page](#)

Refresh Page

[Return to Show Programmed Devices page](#)

### Video Device Management

**Upon submittal, an email confirmation of the transaction will be sent to the end-user.**

Action	Type	Name of Video device	Mac	Last Check In (GMT)	Version
<a href="#">Edit/Delete</a>	IP Camera	OFFICE 1	00C0023DEBA9	Mon, Jun 14 2010 20:25:00	V1.0.08R00
<a href="#">Edit/Delete</a>	IP Camera	Office 2	00C0023DEB9B	Mon, Jun 14 2010 20:25:00	V1.0.08R00
<a href="#">Edit/Delete</a>	IP Camera	Office 3	00C0023DEAC1	Mon, Jun 14 2010 20:25:00	V1.0.08R00
<a href="#">Edit/Delete</a>	IP Camera	Office 4	00C00230E65B	Mon, Jun 14 2010 20:25:00	V1.0.01R00
<a href="#">Edit/Delete</a>	IP Camera	Pan Tilt Office	00C0022E05CA	Mon, Jun 14 2010 20:25:00	V1.0.07R00
<a href="#">Edit/Delete</a>	Optiflex	Total Connect Video	00D02D005572	N/A	N/A

Once cameras are installed you can use the Video Configure option to check the status of a camera and its software version

### Add an IP Camera to Account 89-E4-0500

**VIDEO MAC ID :**  
 -  -  -  -  -

**Video Device Name :**

[Return to Show Programmed Devices page](#)